

FX Projector Daylight - DMX chart

DMX modes

DMX channels ↓	8 channels	4 channels
1	Master Dimmer	Master Dimmer
2	Spare Channel	Animation Wheels Rotation Speed
3	Dimmer Fine	Speed Animation Wheel 1
4	Strobe	Speed Animation Wheel 2
5	Special Function	
6	Animation Wheels Rotation Speed	
7	Speed Animation Wheel 1	
8	Speed Animation Wheel 2	

DMX Chart 8 channels

channel	function	type of control	effect	decimal	percentage
1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0 - 255	0% - 100%
2	spare channel	step	no effect	0 - 255	0% - 100%
3	dimmer fine	proportional	fine dimmer control 16 bit	0 - 255	0% - 100%
4	strobe	step	no effect	0 - 9	0% - 4%
		proportional	variable speed strobing effect, from slow to fast	10 - 57	4% - 22%
		step	stop strobe	58 - 59	23% - 23%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	60 - 108	24% - 42%
		step	stop strobe	109 - 110	43% - 43%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from slow to fast)	111 - 159	44% - 62%
		step	stop strobe	160 - 161	63% - 63%
		proportional	random strobe effect with variable speed from slow to fast	162 - 207	64% - 81%
		step	stop strobe	208 - 209	82% - 82%
		proportional	random strobe effect with variable speed from slow to fast	210 - 255	82% - 100%
5	special functions	step	park	0 - 9	0% - 4%
			600 Hz	10 - 22	4% - 9%
			no effect	23 - 84	9% - 33%
			fan at SILENT mode	85 - 96	33% - 38%
			fan at STUDIO mode	97 - 108	38% - 42%
			fan at AUTO mode	109 - 120	43% - 47%
		proportional	fan speed control	121 - 133	47% - 52%
		step	enables the automatic display blackout	134 - 185	53% - 73%
			disables the automatic display blackout	186 - 199	73% - 78%
			LED control frequency tuning 1.500 Hz	200 - 205	78% - 80%
			LED control frequency tuning 2.000 Hz	206 - 211	81% - 83%
			LED control frequency tuning 5.000 Hz	212 - 217	83% - 85%
			no effect	218 - 240	85% - 94%
			LED control frequency tuning 20.000 Hz	241 - 255	95% - 100%
6	animation wheels rotation speed		proportional	adjust proportionally the speed of both animation wheels	0 - 255
7	speed animation wheel 1	step	animation wheel in stop	0 - 9	0% - 4%
		proportional	control the animation wheel 1 speed counterclockwise (from fast to slow)	10 - 124	4% - 49%
		step	animation wheel in stop	125 - 129	49% - 51%
		proportional	control the animation wheel 1 speed clockwise (from slow to fast)	130 - 245	51% - 96%
		step	animation wheel in stop	246 - 255	97% - 100%
8	speed animation wheel 2	step	animation wheel in stop	0 - 9	0% - 4%
		proportional	control the animation wheel 1 speed counterclockwise (from fast to slow)	10 - 124	4% - 49%
		step	animation wheel in stop	125 - 129	49% - 51%
		proportional	control the animation wheel 1 speed clockwise (from slow to fast)	130 - 245	51% - 96%
		step	animation wheel in stop	246 - 255	97% - 100%

DMX Chart 4 channels

channel	function	type of control	effect	decimal		percentage	
1	master dimmer	proportional	adjust luminous output intensity from 0 to 100%	0	- 255	0%	- 100%
2	gobo rotation speed	proportional	adjust proportionally the speed of both gobos	0	- 255	0%	- 100%
3	speed animation wheel 1	step	animation wheel in stop	0	- 9	0%	- 4%
		proportional	control the animation wheel 1 speed counterclockwise (from fast to slow)	10	- 124	4%	- 49%
		step	animation wheel in stop	125	- 129	49%	- 51%
		proportional	control the animation wheel 1 speed clockwise (from slow to fast)	130	- 245	51%	- 96%
		step	animation wheel in stop	246	- 255	97%	- 100%
4	speed animation wheel 2	step	animation wheel in stop	0	- 9	0%	- 4%
		proportional	control the animation wheel 1 speed counterclockwise (from fast to slow)	10	- 124	4%	- 49%
		step	animation wheel in stop	125	- 129	49%	- 51%
		proportional	control the animation wheel 1 speed clockwise (from slow to fast)	130	- 245	51%	- 96%
		step	animation wheel in stop	246	- 255	97%	- 100%